

Actuating direction	from front	from front	from front	from side	from side
Switch travel					
Contacts Actuating direction	1 change-over contact N or S	1 bistable contact N/S	1 bistable change-over contact N/S	1 bistable contact N or S	1 bistable change-over contact N or S
Actuating magnet	Switching distance [mm] on    off	Switching distance [mm] on    off	Switching distance [mm] on    off	Switching distance [mm] on    off	Switching distance [mm] on    off
M 50 U	4    7	12    6	–    –		–    –
M 100	10    13	22    12	20    40		15    20
M 100 U	10    13	22    12	20    40		15    20
M 200	13    16	30    30	25    50		20    25
M 200 U	13    16	30    30	25    50		20    25
M 300	17    20	37    23	30    60		25    30
M 300 U	17    20	37    23	30    60		25    30
M 400 U	33    37	63    43	50    90		30    35
M 700	30    35	60    40	50    75		40    50